



**POWER BRIGHT**  
YOUR LEADER IN POWER SOLUTIONS

MODEL  
**PW2300-12**

SPECIFICATION SHEET

## 12V DC to AC 2300 Watt Power Inverter

This heavy duty inverter plugs directly to a 12 Volt DC battery to power a small microwave, power tools and electronics in your vehicle!

### This unit has the following features:

- 2300 watts continuous power
- 4600 watts peak power
- Provides 19.2 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 110 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch

**CE** **RoHS**  
COMPLIANT



Optimum efficiency	up to 90%
No-load draw	< 0.2 amp
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	2 - three-prong receptacle
Inverter weight	14.50 lbs
Dimensions (W x H x D)	10.25 x 3.5 x 13.8 in.

MODEL  
**PW2300-12**  
SPECIFICATION SHEET

Find out more about batteries and power sources we have.