



## Inverter Remote Control Modified Sine Wave

Model  
SAM-RC

### Design Features

- Bar Meter Monitor for battery charge level and output power
- LED indicator lights for:
  - Over voltage protection
  - Under voltage protection
  - Over temperature protection
  - Over load protection
  - Power save mode
- Designed for use with the following SAM Series Inverters:
  - SAM-1000-12
  - SAM-1500-12
  - SAM-2000-12
  - SAM-3000-12

## 2 YEAR LIMITED WARRANTY

MODEL NO.	SAM-RC
INPUT VOLTAGE	For 12 V SAM Series inverters
CONNECTING CABLE	RJ-45 (8P8C), straight-through cable; 3 meters / 10 ft
OPERATING TEMPERATURE RANGE	0 - 40°C
STORAGE TEMPERATURE RANGE	- 30°C to + 70°C
DIMENSIONS, INCHES (L x W x H)	4.53 x 2.76 x 1.06"
DIMENSIONS, MM (L x W x H)	115 x 70 x 27 mm

NOTE: Specifications are subject to change without notice